

**PL-TR-95-2037(II)**

## **CIRRIS 1A POST FLIGHT CALIBRATION**

**Gail Bingham  
James Peterson  
Steven Brown  
David Morse  
Brent Bartschi  
Allan Steed**

**Space Dynamics Laboratory/Utah State University  
Logan, Utah 84322**

**January 1995**

**Final Report (Volume II)  
3 June 1981 - 31 May 1994**

**Approved for public release; distribution unlimited**



**PHILLIPS LABORATORY  
Directorate of Geophysics  
AIR FORCE MATERIEL COMMAND  
HANSCOM AFB, MA 01731-3010**

**19961220 115**


**DTIC QUALITY INSPECTED 1**

"This technical report has been reviewed and is approved for publication"




(Signature)

Richard M. Nadile  
Contract Manager



(Signature)

Dr. Stephen D. Price  
Branch Chief



(Signature)

Dr. Roger A. Van Tassel  
Division Director

This report has been reviewed by the ESC Public Affairs Office (PA) and is releasable to the National Technical Information Service (NTIS).

Qualified requestors may obtain additional copies from the Defense Technical Information Center (DTIC). All others should apply to the National Technical Information Service (NTIS).

If your address has changed, if you wish to be removed from the mailing list, or if the addressee is no longer employed by your organization, please notify PL/IM, 29 Randolph Road, Hanscom AFB, MA 01731-3010. This will assist us in maintaining a current mailing list.

Do not return copies of this report unless contractual obligations or notices on a specific document requires that it be returned.

# REPORT DOCUMENTATION PAGE

Form Approved  
OMB No. 0704-0188

Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.

1. AGENCY USE ONLY (Leave blank)		2. REPORT DATE January 1995		3. REPORT TYPE AND DATES COVERED Final Vol II (3 Jun 1981-31 May 1994)	
4. TITLE AND SUBTITLE  CIRRIS 1A Post Flight Calibration				5. FUNDING NUMBERS  PE 62101F PR 7670 TA 10 WU AI  Contract F19628-81-C-0123	
6. AUTHOR(S) Gail Bingham                      David Morse James Peterson                  Brent Bartschi Steven Brown                    Allan Steed					
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES)  Space Dynamics Laboratory Utah State University Logan, Utah 84341				8. PERFORMING ORGANIZATION REPORT NUMBER  SDL/92-091	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES) Phillips Laboratory 29 Randolph Road Hanscom AFB, MA 01731-3010 Contract Manager: Richard Nadile (GPOB)				10. SPONSORING/MONITORING AGENCY REPORT NUMBER  PL-TR-95-2037 (II)	
11. SUPPLEMENTARY NOTES					
12a. DISTRIBUTION/AVAILABILITY STATEMENT  Approved for public release; distribution unlimited				12b. DISTRIBUTION CODE	
13. ABSTRACT (Maximum 200 words)  The Cryogenic Infrared Radiance Instrumentation for Shuttle (CIRRIS 1A) instrument is a state-of-the-art cryogenically cooled instrument designed to observe the infrared spectrum of the earth's atmosphere. The Space Dynamics Laboratory at Utah State University (SDL/USU) participated as the prime contractor in this program. CIRRIS 1A was launched on the shuttle Discovery (STS-39) on 28 April 1991. All of the instruments operated as designed during the mission. Data obtained from this experiment will help refine knowledge of the background radiance and structure of atmospheric infrared emissions, and will be used to update and validate U.S. Air Force atmospheric models used in the design of operational systems. SDL/USU performed a complete ground calibration of the primary and ancillary sensors to verify instrument design and to create algorithms necessary for post flight data reduction. This report represents Volume 2 of the CIRRIS 1A Post Flight Calibration Final Report. Volume 2 contains reduced data for various parameters for all of the detectors. Volume 1 describes the calibration approach, discusses the results of the calibration, and provides graphical data for the primary detectors of each sensor. General descriptions of the radiometer and interferometer are also included.					
14. SUBJECT TERMS  CIRRIS 1A, calibration, radiometer, interferometer, infrared, shuttle				15. NUMBER OF PAGES 78	
				16. PRICE CODE	
17. SECURITY CLASSIFICATION OF REPORT  Unclassified	18. SECURITY CLASSIFICATION OF THIS PAGE  Unclassified	19. SECURITY CLASSIFICATION OF ABSTRACT  Unclassified	20. LIMITATION OF ABSTRACT  SAR		

## LIST OF FIGURES

	<u>Page</u>
Jones source maps for radiometer detectors 1-1 and 1-2. ....	1
Jones source maps for radiometer detectors 1-3 and 1-4. ....	2
Jones source maps for radiometer detectors 1-5 and 1-6. ....	3
Jones source maps for radiometer detectors 1-7 and 1-8. ....	4
Jones source maps for radiometer detectors 2-1 and 2-2. ....	5
Jones source maps for radiometer detectors 2-3 and 2-4. ....	6
Jones source maps for radiometer detectors 2-5. ....	7
Relative spectral response for radiometer detector 1-4. ....	16
Relative spectral response for radiometer focal plane 2. ....	18
Radiometer out-of-band rejection, focal plane 1, filter 0. ....	19
Radiometer out-of-band rejection, focal plane 1, filter 1. ....	19
Radiometer out-of-band rejection, focal plane 1, filter 2. ....	20
Radiometer out-of-band rejection, focal plane 1, filter 3. ....	20
Radiometer out-of-band rejection, focal plane 1, filter 5. ....	21
Radiometer out-of-band rejection, focal plane 1, filter 7. ....	21
Radiometer out-of-band rejection, focal plane 2. ....	22
RMS noise history for radiometer detector 1-1. ....	23
RMS noise history for radiometer detector 1-2. ....	24
RMS noise history for radiometer detector 1-3. ....	25
RMS noise history for radiometer detector 1-4. ....	26
RMS noise history for radiometer detector 1-5. ....	27
RMS noise history for radiometer detector 1-6. ....	28
RMS noise history for radiometer detector 1-7. ....	29
RMS noise history for radiometer detector 1-8. ....	30
RMS noise history for radiometer detector 2-1. ....	31
RMS noise history for radiometer detector 2-2. ....	32
RMS noise history for radiometer detector 2-3. ....	33
RMS noise history for radiometer detector 2-4. ....	34
RMS noise history for radiometer detector 2-5. ....	35
Offset history for radiometer detector 1-1. ....	36

Offset history for radiometer detector 1-2. ....	37
Offset history for radiometer detector 1-3. ....	38
Offset history for radiometer detector 1-4. ....	39
Offset history for radiometer detector 1-5. ....	40
Offset history for radiometer detector 1-6. ....	41
Offset history for radiometer detector 1-7. ....	42
Offset history for radiometer detector 1-8. ....	43
Offset history for radiometer detector 2-1. ....	44
Offset history for radiometer detector 2-2. ....	45
Offset history for radiometer detector 2-3. ....	46
Offset history for radiometer detector 2-4. ....	47
Offset history for radiometer detector 2-5. ....	48
Radiometer noise flux versus band pass for filter 0 (chopper on, extended area source - order on curve labels is bias - gain). ....	49
Radiometer noise flux versus band pass for filter 0 (chopper on, extended area source - order on curve labels is bias - gain). ....	50
Radiometer noise flux versus band pass for filter 1 (chopper on, extended area source - order on curve labels is bias - gain). ....	51
Radiometer noise flux versus band pass for filter 1 (chopper on, extended area source - order on curve labels is bias - gain). ....	52
Radiometer noise flux versus band pass for filter 2 (chopper on, extended area source - order on curve labels is bias - gain). ....	53
Radiometer noise flux versus band pass for filter 2 (chopper on, extended area source - order on curve labels is bias - gain). ....	54
Radiometer noise flux versus band pass for filter 3 (chopper on, extended area source - order on curve labels is bias - gain). ....	55
Radiometer noise flux versus band pass for filter 3 (chopper on, extended area source - order on curve labels is bias - gain). ....	56
Radiometer noise flux versus band pass for filter 5 (chopper on, extended area source - order on curve labels is bias - gain). ....	57
Radiometer noise flux versus band pass for filter 5 (chopper on, extended area source - order on curve labels is bias - gain). ....	58
Radiometer noise flux versus band pass for filter 6 (chopper on, extended area source - order on curve labels is bias - gain). ....	59
Radiometer noise flux versus band pass for filter 6 (chopper on, extended area source - order on curve labels is bias - gain). ....	60

Radiometer noise flux versus band pass for filter 7 (chopper on, extended area source - order on curve labels is bias - gain). .....	61
Radiometer noise flux versus band pass for filter 7 (chopper on, extended area source - order on curve labels is bias - gain). .....	62
Radiometer noise flux versus band pass (chopper on, extended area source - order on curve labels is bias - gain). .....	63
Radiometer noise flux versus band pass (chopper on, extended area source - order on curve labels is bias - gain). .....	64
RMS noise history for interferometer detector 1. ....	65
RMS noise history for interferometer detector 2. ....	65
RMS noise history for interferometer detector 3. ....	66
RMS noise history for interferometer detector 4. ....	66
RMS noise history for interferometer detector 5. ....	67
Offset history for interferometer detector 1. ....	68
Offset history for interferometer detector 2. ....	68
Offset history for interferometer detector 3. ....	69
Offset history for interferometer detector 4. ....	69
Offset history for interferometer detector 5. ....	70


## FOREWORD

The Cryogenic Infrared Radiance Instrumentation for Shuttle (CIRRIS 1A) program, sponsored by the Strategic Defense Initiative Organization (SDIO) and managed by the Geophysics Directorate of the USAF Phillips Laboratory, is a state-of-the-art cryogenically cooled instrument designed to observe the infrared spectrum of the earth's atmosphere. The Space Dynamics Laboratory at Utah State University (SDL/USU) was awarded contract no. F19628-81-C-0123 to participate as the prime contractor in this program. As part of this program, SDL designed, constructed, calibrated, tested, and integrated primary and support instruments for the CIRRIS 1A experiment. In addition, SDL personnel provided mission support and documentation, including flight crew training. CIRRIS 1A was launched on the space shuttle Discovery on 28 April 1991. All of the instruments operated as designed during the mission.


This report, submitted in compliance with CDRL 160, presents the results of the CIRRIS 1A post flight calibration. This document represents the current understanding of the CIRRIS 1A calibration accuracy and applicability to the data collected during the CIRRIS mission. Several drafts of this report were previously submitted for review; this document is the final submission. The calibration coefficients will continue to be refined as the flight data are further analyzed.

This document represents Volume 2 of the CIRRIS 1A Post Flight Calibration Final Report. This volume contains reduced data for various parameters for all of the detectors. The calibration approach and results are presented in Volume 1.

SDL/USU would like to acknowledge Boston College, Miranda Laboratories, and PhotoMetrics for alignment and pointing data, and coding of OPUS.




DESCRIPTION  
 Detector... 1-1L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum 0.00000  
 Maximum 0.14199  
 D:\RPSMAP10\M10D11L



DESCRIPTION  
 Detector... 1-2L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum 0.00009  
 Maximum 0.13251  
 D:\RPSMAP10\M10D12L


Jones source maps for radiometer detectors 1-1 and 1-2.





#### DESCRIPTION


Detector... 1-3L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum -0.00008  
 Maximum 0.12249  
 D:\RPSMAP10\M10D13L



#### DESCRIPTION


Detector... 1-4L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum 0.00013  
 Maximum 0.14037  
 D:\RPSMAP10\M10D14L

Jones source maps for radiometer detectors 1-3 and 1-4.




DESCRIPTION  
 Detector... 1-5L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum -0.00079  
 Maximum 0.12647  
 D:\RPSMAP10\M10D15L


Jones source maps for radiometer detectors 1-5 and 1-6.



DESCRIPTION  
 Detector... 1-6L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum -0.00013  
 Maximum 0.12991  
 D:\RPSMAP10\M10D16L




DESCRIPTION  
 Detector.... 1-7L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X..... 5.00  
 Delta Y..... 5.00  
 Minimum -0.00024  
 Maximum 0.01079  
 D:\RPSMAP10\M10D17L




DESCRIPTION  
 Detector.... 1-8L  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X..... 5.00  
 Delta Y..... 5.00  
 Minimum -0.00018  
 Maximum 0.01789  
 D:\RPSMAP10\M10D18L

Jones source maps for radiometer detectors 1-7 and 1-8.




DESCRIPTION  
 Detector... 2-1H  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum -0.00277  
 Maximum 0.29134  
 D:\RPSMAP10\M10D21H




DESCRIPTION  
 Detector... 2-2H  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum -0.005535  
 Maximum 1.56265  
 D:\RPSMAP10\M10D22H

Jones source maps for radiometer detectors 2-1 and 2-2.




DESCRIPTION  
 Detector... 2-3H  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum -0.00277  
 Maximum 0.19387  
 D:\RPSMAP10\M10D23H



DESCRIPTION  
 Detector... 2-4H  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X... 5.00  
 Delta Y... 5.00  
 Minimum -0.00331  
 Maximum 0.03585  
 D:\RPSMAP10\M10D24H

Jones source maps for radiometer detectors 2-3 and 2-4.



DESCRIPTION  
 Detector.... 2-5H  
 Starting X... 0.00  
 Starting Y... -240.00  
 Number of X... 21  
 Number of Y... 31  
 Delta X.... 5.00  
 Delta Y.... 5.00  
 Minimum -0.00305  
 Maximum 0.13269  
 D:\RPSMAP10\N10D25+

Jones source maps for radiometer detectors 2-5.

**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 1, filter 0, bandpass, linear fit)

DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
1-1	HI	LO	4.04044E+00	-4.06883E-01	1.97368E-04	5.90900E-04	1.59300E+00
1-2			2.15022E+00	-2.16524E-01	1.97925E-04	5.90900E-04	1.59300E+00
1-3			4.86650E+00	-4.90052E-01	1.97816E-04	5.90900E-04	1.59300E+00
1-4			2.07024E+00	-2.08483E-01	1.97037E-04	5.90900E-04	1.59300E+00
1-5			5.00050E+00	-5.03538E-01	1.98077E-04	5.90900E-04	1.59300E+00
1-6			2.03032E+00	-2.04303E-01	1.60217E-02	5.90900E-04	1.59300E+00
1-7			7.39075E+01	-7.44237E+00	1.97930E-04	5.90900E-04	1.59300E+00
1-8			1.75018E+01	-1.76244E+00	1.97691E-04	5.90900E-04	1.59300E+00
1-1	HI	HI	4.07042E-02	-4.09890E-03	1.97782E-04	5.90900E-04	1.59300E+00
1-2			2.50027E-02	-2.51783E-03	1.97397E-04	5.90900E-04	1.59300E+00
1-3			5.00054E-02	-5.03565E-03	1.97397E-04	5.90900E-04	1.59300E+00
1-4			2.14022E-02	-2.15520E-03	1.97737E-04	5.90900E-04	1.59300E+00
1-5			5.30055E-02	-5.33764E-03	1.97733E-04	5.90900E-04	1.59300E+00
1-6			2.13023E-02	-2.14517E-03	1.97491E-04	5.90900E-04	1.59300E+00
1-7			7.60085E-01	-7.65435E-02	1.97162E-04	5.90900E-04	1.59300E+00
1-8			1.95020E-01	-1.96384E-02	1.97798E-04	5.90900E-04	1.59300E+00
1-1	MED	LO	3.03414E+01	0.00000E+00	3.13351E-03	1.49600E-01	6.12700E-01
1-2			1.71432E+01	0.00000E+00	3.10408E-03	2.72600E-01	1.09300E+00
1-3			3.16675E+01	0.00000E+00	1.10090E-02	1.43500E-01	5.86800E-01
1-4			1.57333E+01	0.00000E+00	4.32499E-03	2.98000E-01	1.19200E+00
1-5			3.60025E+01	0.00000E+00	2.35026E-03	1.26700E-01	5.17200E-01
1-6			1.51775E+01	0.00000E+00	1.06077E-02	3.14700E-01	1.80100E+00
1-7			5.84064E+02	0.00000E+00	6.15571E-03	8.06100E-03	4.67200E-02
1-8			1.16936E+02	0.00000E+00	2.67001E-03	3.83000E-02	2.31100E-01
1-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	LO	2.89243E+02	0.00000E+00	1.91450E-02	9.81800E-02	2.27600E+00
1-2			1.60492E+02	0.00000E+00	1.54137E-02	1.74400E-01	1.97400E+00
1-3			3.13617E+02	0.00000E+00	3.04576E-02	9.05800E-02	2.09500E+00
1-4			1.46450E+02	0.00000E+00	1.95774E-02	1.87300E-01	2.16500E+00
1-5			3.46726E+02	0.00000E+00	3.67822E-02	8.16700E-02	1.89400E+00
1-6			1.41526E+02	0.00000E+00	7.86006E-03	2.92700E-01	2.25100E+00
1-7			5.89601E+03	0.00000E+00	5.77316E-02	1.81800E-02	1.32600E+00
1-8			1.11848E+03	0.00000E+00	3.80401E-02	3.75300E-02	2.17600E+00
1-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00

**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 1, filter 1, bandpass, linear fit)

DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
1-1	HI	LO	2.80030E+01	-2.81996E+00	1.97384E-04	5.90900E-04	1.59300E+00
1-2			1.55017E+01	-1.56104E+00	1.97421E-04	5.90900E-04	1.59300E+00
1-3			3.97043E+01	-3.99830E+00	1.97423E-04	5.90900E-04	1.59300E+00
1-4			1.55017E+01	-1.56104E+00	1.97421E-04	5.90900E-04	1.59300E+00
1-5			4.14044E+01	-4.16949E+00	1.97512E-04	5.90900E-04	1.59300E+00
1-6			1.67018E+01	-1.68191E+00	1.97469E-04	5.90900E-04	1.59300E+00
1-7			6.27063E+02	-6.31440E+01	1.98031E-04	5.90900E-04	1.59300E+00
1-8			1.25014E+02	-1.25894E+01	1.97146E-04	5.90900E-04	1.59300E+00
1-1	HI	HI	2.80033E-01	-2.82011E-02	1.96884E-04	5.90900E-04	1.59300E+00
1-2			1.59017E-01	-1.60134E-02	1.97363E-04	5.90900E-04	1.59300E+00
1-3			3.90040E-01	-3.92769E-02	1.97798E-04	5.90900E-04	1.59300E+00
1-4			1.48016E-01	-1.49055E-02	1.97410E-04	5.90900E-04	1.59300E+00
1-5			4.20045E-01	-4.22995E-02	1.97428E-04	5.90900E-04	1.59300E+00
1-6			1.62018E-01	-1.63155E-02	1.97374E-04	5.90900E-04	1.59300E+00
1-7			6.40069E+00	-6.44564E-01	1.97397E-04	5.90900E-04	1.59300E+00
1-8			1.35015E+00	-1.35968E-01	1.96995E-04	5.90900E-04	1.59300E+00
1-1	MED	LO	2.35997E+02	0.00000E+00	2.79648E-03	9.06500E-02	2.07600E-01
1-2			1.30052E+02	0.00000E+00	3.13445E-03	1.64400E-01	3.76600E-01
1-3			2.93441E+02	0.00000E+00	2.63949E-03	7.30400E-02	1.67100E-01
1-4			1.25395E+02	0.00000E+00	2.83262E-03	1.70000E-01	3.90100E-01
1-5			3.26714E+02	0.00000E+00	2.26316E-03	6.56100E-02	1.50100E-01
1-6			1.31515E+02	0.00000E+00	3.78212E-03	1.61400E-01	3.71200E-01
1-7			5.34756E+03	0.00000E+00	4.22618E-03	4.02300E-03	9.18200E-03
1-8			9.20928E+02	0.00000E+00	3.87946E-03	2.28700E-02	5.28300E-02
1-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	LO	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00



**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 1, filter 2, bandpass, linear fit)

DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
1-1	HI	LO	1.33714E+01	-1.34651E+00	1.97620E-04	5.90900E-04	1.59300E+00
1-2			7.25076E+00	-7.30156E-01	1.97613E-04	5.90900E-04	1.59300E+00
1-3			1.80019E+01	-1.81282E+00	1.97455E-04	5.90900E-04	1.59300E+00
1-4			6.90067E+00	-6.94871E-01	1.98314E-04	5.90900E-04	1.59300E+00
1-5			1.82020E+01	-1.83299E+00	1.97327E-04	5.90900E-04	1.59300E+00
1-6			7.40082E+00	-7.45290E-01	1.97228E-04	5.90900E-04	1.59300E+00
1-7			2.99033E+02	-3.01135E+01	1.97265E-04	5.90900E-04	1.59300E+00
1-8			6.00063E+01	-6.04266E+00	1.97633E-04	5.90900E-04	1.59300E+00
1-1	HI	HI	1.38014E-01	-1.38979E-02	1.97872E-04	5.90900E-04	1.59300E+00
1-2			7.20077E-02	-7.25131E-03	1.97468E-04	5.90900E-04	1.59300E+00
1-3			1.80019E-01	-1.81278E-02	1.97757E-04	5.90900E-04	1.59300E+00
1-4			7.10068E-02	-7.15008E-03	1.98484E-04	5.90900E-04	1.59300E+00
1-5			1.87020E-01	-1.88330E-02	1.97654E-04	5.90900E-04	1.59300E+00
1-6			7.40080E-02	-7.45275E-03	1.97410E-04	5.90900E-04	1.59300E+00
1-7			3.00033E+00	-3.02140E-01	1.97367E-04	5.90900E-04	1.59300E+00
1-8			6.50067E-01	-6.54615E-02	1.97751E-04	5.90900E-04	1.59300E+00
1-1	MED	LO	1.11696E+02	0.00000E+00	3.21374E-03	1.16300E-01	6.17400E-01
1-2			6.13877E+01	0.00000E+00	3.01686E-03	2.13800E-01	1.12600E+00
1-3			1.31834E+02	0.00000E+00	4.19463E-03	9.78100E-02	5.22300E-01
1-4			5.77732E+01	0.00000E+00	8.64858E-03	2.25400E-01	1.19600E+00
1-5			1.43980E+02	0.00000E+00	1.38927E-03	9.06200E-02	4.79400E-01
1-6			5.99653E+01	0.00000E+00	5.20095E-03	4.03800E-01	1.81500E+00
1-7			2.55910E+03	0.00000E+00	1.60595E-03	9.25800E-03	4.23100E-02
1-8			4.42348E+02	0.00000E+00	3.37276E-03	5.17800E-02	2.42900E-01
1-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	LO	1.04860E+03	0.00000E+00	9.60681E-03	1.02700E-01	1.11300E+00
1-2			5.78827E+02	0.00000E+00	1.80986E-03	1.87400E-01	2.03100E+00
1-3			1.26108E+03	0.00000E+00	5.18505E-03	8.61500E-02	9.31900E-01
1-4			5.34755E+02	0.00000E+00	4.64426E-03	1.98000E-01	2.19400E+00
1-5			1.33989E+03	0.00000E+00	6.63744E-03	7.98600E-02	8.74100E-01
1-6			5.64736E+02	0.00000E+00	5.48157E-03	3.00000E-01	2.08800E+00
1-7			2.32690E+04	0.00000E+00	4.17668E-03	7.08400E-03	5.03600E-02
1-8			4.01611E+03	0.00000E+00	5.35184E-03	4.09500E-02	2.92500E-01
1-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00

**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 1, filter 3, bandpass, linear fit)

DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
1-1	HI	LO	9.24095E+00	-9.30558E-01	1.97804E-04	5.90900E-04	1.59300E+00
1-2			5.10054E+00	-5.13630E-01	1.97565E-04	5.90900E-04	1.59300E+00
1-3			1.19013E+01	-1.19850E+00	1.97282E-04	5.90900E-04	1.59300E+00
1-4			4.72049E+00	-4.75355E-01	1.97683E-04	5.90900E-04	1.59300E+00
1-5			1.18013E+01	-1.18845E+00	1.97075E-04	5.90900E-04	1.59300E+00
1-6			4.85057E+00	-4.88485E-01	1.96858E-04	5.90900E-04	1.59300E+00
1-7			2.00020E+02	-2.01415E+01	1.98138E-04	5.90900E-04	1.59300E+00
1-8			4.20044E+01	-4.22984E+00	1.97709E-04	5.90900E-04	1.59300E+00
1-1	HI	HI	1.00011E-01	-1.00713E-02	1.97397E-04	5.90900E-04	1.59300E+00
1-2			5.50060E-02	-5.53925E-03	1.97351E-04	5.90900E-04	1.59300E+00
1-3			1.28014E-01	-1.28911E-02	1.97547E-04	5.90900E-04	1.59300E+00
1-4			5.00054E-02	-5.03565E-03	1.97397E-04	5.90900E-04	1.59300E+00
1-5			1.26014E-01	-1.26902E-02	1.97119E-04	5.90900E-04	1.59300E+00
1-6			5.10053E-02	-5.13625E-03	1.97680E-04	5.90900E-04	1.59300E+00
1-7			2.05020E+00	-2.06449E-01	1.98214E-04	5.90900E-04	1.59300E+00
1-8			4.60049E-01	-4.63273E-02	1.97570E-04	5.90900E-04	1.59300E+00
1-1	MED	LO	7.64607E+01	0.00000E+00	4.13072E-03	1.24000E-01	8.06100E-01
1-2			4.33221E+01	0.00000E+00	2.41812E-03	2.24700E-01	1.42900E+00
1-3			8.56132E+01	0.00000E+00	1.11518E-02	1.12200E-01	7.20600E-01
1-4			3.96118E+01	0.00000E+00	2.80515E-03	2.49300E-01	1.56700E+00
1-5			9.16161E+01	0.00000E+00	4.00900E-03	1.04700E-01	6.73900E-01
1-6			3.93271E+01	0.00000E+00	7.89901E-03	2.53600E-01	1.58100E+00
1-7			1.66104E+03	0.00000E+00	2.68353E-03	5.92200E-03	3.73200E-02
1-8			3.06200E+02	0.00000E+00	3.60119E-03	3.09200E-02	2.01200E-01
1-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	LO	7.38846E+02	0.00000E+00	2.16146E-02	1.38100E-01	2.03100E+00
1-2			4.09153E+02	0.00000E+00	6.01879E-04	2.46500E-01	2.17100E+00
1-3			8.39453E+02	0.00000E+00	1.66609E-02	1.21900E-01	2.27900E+00
1-4			3.71243E+02	0.00000E+00	4.36598E-03	2.73600E-01	2.39200E+00
1-5			8.91141E+02	0.00000E+00	2.44889E-02	1.15000E-01	2.15500E+00
1-6			3.74388E+02	0.00000E+00	6.49464E-03	2.74600E-01	2.38600E+00
1-7			1.52544E+04	0.00000E+00	9.91429E-03	6.59300E-03	1.58200E-01
1-8			2.80288E+03	0.00000E+00	2.98728E-03	3.57400E-02	8.61300E-01
1-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00

**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 1, filter 5, bandpass, linear fit)

DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
1-1	HI	LO	4.70050E+00	-4.73345E-01	1.97572E-04	5.90900E-04	1.59300E+00
1-2			2.62027E+00	-2.63858E-01	1.97887E-04	5.90900E-04	1.59300E+00
1-3			5.70063E+00	-5.74074E-01	1.97235E-04	5.90900E-04	1.59300E+00
1-4			2.44027E+00	-2.45745E-01	1.97171E-04	5.90900E-04	1.59300E+00
1-5			5.90067E+00	-5.94225E-01	1.97075E-04	5.90900E-04	1.59300E+00
1-6			2.45028E+00	-2.46758E-01	1.96919E-04	5.90900E-04	1.59300E+00
1-7			9.20098E+01	-9.26551E+00	1.97514E-04	5.90900E-04	1.59300E+00
1-8			2.10022E+01	-2.11492E+00	1.97709E-04	5.90900E-04	1.59300E+00
1-1	HI	HI	5.15055E-02	-5.18668E-03	1.97471E-04	5.90900E-04	1.59300E+00
1-2			2.95031E-02	-2.97097E-03	1.97681E-04	5.90900E-04	1.59300E+00
1-3			6.30071E-02	-6.34508E-03	1.97119E-04	5.90900E-04	1.59300E+00
1-4			2.70029E-02	-2.71922E-03	1.97529E-04	5.90900E-04	1.59300E+00
1-5			6.50073E-02	-6.54648E-03	1.97123E-04	5.90900E-04	1.59300E+00
1-6			2.70029E-02	-2.71922E-03	1.97529E-04	5.90900E-04	1.59300E+00
1-7			9.70109E-01	-9.76943E-02	1.97145E-04	5.90900E-04	1.59300E+00
1-8			2.45026E-01	-2.46745E-02	1.97475E-04	5.90900E-04	1.59300E+00
1-1	MED	LO	3.76153E+01	0.00000E+00	6.88971E-03	1.31600E-01	6.84200E-01
1-2			2.16678E+01	0.00000E+00	5.06421E-03	2.31200E-01	1.19100E+00
1-3			3.99215E+01	0.00000E+00	9.31075E-03	1.21600E-01	6.41800E-01
1-4			1.96088E+01	0.00000E+00	5.30408E-03	2.56300E-01	1.31700E+00
1-5			4.42227E+01	0.00000E+00	8.62833E-03	1.10300E-01	5.79700E-01
1-6			1.90596E+01	0.00000E+00	6.37522E-03	2.64900E-01	1.35700E+00
1-7			7.68690E+02	0.00000E+00	9.28259E-03	6.50100E-03	3.35500E-02
1-8			1.52497E+02	0.00000E+00	6.48132E-03	3.15900E-02	1.67900E-01
1-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	LO	3.61336E+02	0.00000E+00	9.55926E-03	1.17700E-01	2.19700E+00
1-2			2.06561E+02	0.00000E+00	4.32410E-03	2.06700E-01	2.62000E+00
1-3			3.94388E+02	0.00000E+00	1.90992E-02	1.09000E-01	2.41600E+00
1-4			1.86299E+02	0.00000E+00	8.65719E-03	2.29400E-01	2.32800E+00
1-5			4.32396E+02	0.00000E+00	1.42712E-02	9.88200E-02	2.19900E+00
1-6			1.83914E+02	0.00000E+00	9.96345E-03	2.35500E-01	2.34700E+00
1-7			7.15619E+03	0.00000E+00	9.91052E-03	5.85000E-03	2.10900E-01
1-8			1.42175E+03	0.00000E+00	3.34997E-03	2.97100E-02	1.07600E+00
1-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00

**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 1, filter 6, bandpass, linear fit)


DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
1-1	HI	LO	2.74029E+00	-2.75951E-01	1.97556E-04	5.90900E-04	1.59300E+00
1-2			1.43015E+00	-1.44020E-01	1.97396E-04	5.90900E-04	1.59300E+00
1-3			3.07035E+00	-3.09198E-01	1.97079E-04	5.90900E-04	1.59300E+00
1-4			1.40015E+00	-1.40995E-01	1.97646E-04	5.90900E-04	1.59300E+00
1-5			3.58042E+00	-3.60570E-01	1.96903E-04	5.90900E-04	1.59300E+00
1-6			1.35015E+00	-1.35968E-01	1.96995E-04	5.90900E-04	1.59300E+00
1-7			5.10051E+01	-5.13611E+00	1.98007E-04	5.90900E-04	1.59300E+00
1-8			1.18013E+01	-1.18845E+00	1.97075E-04	5.90900E-04	1.59300E+00
1-1	HI	HI	2.85028E-02	-2.87014E-03	1.98150E-04	5.90900E-04	1.59300E+00
1-2			1.70018E-02	-1.71211E-03	1.97481E-04	5.90900E-04	1.59300E+00
1-3			3.20034E-02	-3.22278E-03	1.97547E-04	5.90900E-04	1.59300E+00
1-4			1.75020E-02	-1.76257E-03	1.96884E-04	5.90900E-04	1.59300E+00
1-5			3.75039E-02	-3.77662E-03	1.97761E-04	5.90900E-04	1.59300E+00
1-6			1.40015E-02	-1.41000E-03	1.97258E-04	5.90900E-04	1.59300E+00
1-7			5.30059E-01	-5.33787E-02	1.97195E-04	5.90900E-04	1.59300E+00
1-8			1.25014E-01	-1.25892E-02	1.97349E-04	5.90900E-04	1.59300E+00
1-1	MED	LO	2.09710E+01	0.00000E+00	2.34889E-02	1.08100E-01	6.76200E-01
1-2			1.17344E+01	0.00000E+00	1.97782E-02	2.01900E-01	1.22000E+00
1-3			2.17983E+01	0.00000E+00	1.91173E-02	1.04800E-01	6.53400E-01
1-4			1.11109E+01	0.00000E+00	2.06169E-02	2.12000E-01	1.29100E+00
1-5			2.60926E+01	0.00000E+00	1.77302E-02	8.87200E-02	5.47200E-01
1-6			1.10344E+01	0.00000E+00	3.33182E-02	4.05000E-01	1.87000E+00
1-7			4.13411E+02	0.00000E+00	3.41095E-02	9.18700E-03	4.79800E-02
1-8			8.49784E+01	0.00000E+00	2.21705E-02	4.85000E-02	2.38800E-01
1-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	LO	2.37092E+02	0.00000E+00	5.11210E-02	1.31600E-01	2.37400E+00
1-2			1.25615E+02	0.00000E+00	3.61761E-02	1.76800E-01	2.33900E+00
1-3			2.46703E+02	0.00000E+00	5.46204E-02	1.26100E-01	2.29800E+00
1-4			1.19401E+02	0.00000E+00	4.34231E-02	1.82600E-01	2.46300E+00
1-5			2.91423E+02	0.00000E+00	5.23084E-02	1.39300E-01	1.94100E+00
1-6			1.12079E+02	0.00000E+00	3.31469E-02	2.71300E-01	2.00200E+00
1-7			4.63155E+03	0.00000E+00	4.69627E-02	1.48200E-02	4.47100E-01
1-8			9.07261E+02	0.00000E+00	5.90044E-02	3.45300E-02	2.26300E+00
1-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00

**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 1, filter 7, bandpass, linear fit)



DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
1-1	HI	LO	4.93058E+00	-4.96540E-01	1.96893E-04	5.90900E-04	1.59300E+00
1-2			2.59029E+00	-2.60854E-01	1.97106E-04	5.90900E-04	1.59300E+00
1-3			6.10067E+00	-6.14355E-01	1.97291E-04	5.90900E-04	1.59300E+00
1-4			2.45028E+00	-2.46758E-01	1.96919E-04	5.90900E-04	1.59300E+00
1-5			6.28071E+00	-6.32495E-01	1.97080E-04	5.90900E-04	1.59300E+00
1-6			2.48528E+00	-2.50278E-01	1.97120E-04	5.90900E-04	1.59300E+00
1-7			1.00010E+02	-1.00708E+01	1.98138E-04	5.90900E-04	1.59300E+00
1-8			2.27022E+01	-2.28602E+00	1.98375E-04	5.90900E-04	1.59300E+00
1-1	HI	HI	5.20054E-02	-5.23694E-03	1.97785E-04	5.90900E-04	1.59300E+00
1-2			2.87031E-02	-2.89046E-03	1.97414E-04	5.90900E-04	1.59300E+00
1-3			6.35065E-02	-6.39504E-03	1.97887E-04	5.90900E-04	1.59300E+00
1-4			2.53027E-02	-2.54804E-03	1.97436E-04	5.90900E-04	1.59300E+00
1-5			6.53071E-02	-6.57660E-03	1.97350E-04	5.90900E-04	1.59300E+00
1-6			2.65027E-02	-2.66882E-03	1.97733E-04	5.90900E-04	1.59300E+00
1-7			1.05011E+00	-1.05746E-01	1.97716E-04	5.90900E-04	1.59300E+00
1-8			2.40026E-01	-2.41713E-02	1.97319E-04	5.90900E-04	1.59300E+00
1-1	MED	LO	4.02599E+01	0.00000E+00	8.52661E-03	7.12500E-02	2.64800E-01
1-2			2.22169E+01	0.00000E+00	5.83285E-03	1.30000E-01	4.80900E-01
1-3			4.40717E+01	0.00000E+00	6.76410E-03	6.50800E-02	2.41900E-01
1-4			1.98978E+01	0.00000E+00	5.45587E-03	1.44500E-01	5.36200E-01
1-5			4.77429E+01	0.00000E+00	6.33491E-03	5.99500E-02	2.23200E-01
1-6			1.98131E+01	0.00000E+00	1.25351E-02	1.47800E-01	1.56200E+00
1-7			8.26340E+02	0.00000E+00	5.55579E-03	3.52800E-03	3.73800E-02
1-8			1.57822E+02	0.00000E+00	1.19112E-02	1.76200E-02	1.94800E-01
1-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-1	LO	LO	3.95411E+02	0.00000E+00	4.25188E-02	4.12300E-02	2.11700E+00
1-2			2.15415E+02	0.00000E+00	7.30950E-03	7.50800E-02	2.17200E+00
1-3			4.34721E+02	0.00000E+00	4.95090E-02	3.74800E-02	1.92600E+00
1-4			1.93037E+02	0.00000E+00	2.57777E-02	8.22200E-02	2.42500E+00
1-5			4.65179E+02	0.00000E+00	4.67937E-02	3.53400E-02	1.80100E+00
1-6			1.92070E+02	0.00000E+00	4.97299E-03	2.92000E-01	2.44300E+00
1-7			8.08514E+03	0.00000E+00	3.38883E-02	6.94700E-03	4.71200E-01
1-8			1.50470E+03	0.00000E+00	1.28024E-02	3.69300E-02	2.12600E+00
1-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-6			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-7			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
1-8			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00

**CIRRIS 1A Radiometer Linearity Coefficients**  
(focal plane 2, bandpass, linear fit)


DET	BIAS	GAIN	A1	A2	S.D.	MIN. VOLT.	MAX. VOLT.
2-1	HI	LO	7.41184E+01	0.00000E+00	5.88644E-02	6.32100E-04	6.68600E-02
2-2			6.88387E+01	0.00000E+00	5.85583E-02	2.58900E-03	7.09700E-02
2-3			9.80041E+01	0.00000E+00	5.52881E-02	1.64700E-04	5.03700E-02
2-4			6.90045E+02	0.00000E+00	5.53125E-02	3.36700E-04	7.23500E-03
2-5			4.39361E+02	0.00000E+00	4.58320E-02	3.90800E-05	1.12400E-02
2-1	HI	HI	7.23608E-01	0.00000E+00	5.86193E-02	1.15300E-02	1.19700E+00
2-2			6.90780E-01	0.00000E+00	8.50120E-03	1.08200E+00	2.16200E+00
2-3			9.76887E-01	0.00000E+00	4.74408E-02	1.65800E-02	8.78600E-01
2-4			6.86356E+00	0.00000E+00	5.43467E-02	6.78200E-03	7.22400E-01
2-5			4.41210E+00	0.00000E+00	5.66832E-02	4.64700E-03	6.46900E-01
2-1	MED	LO	8.12429E+02	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-2			8.43696E+02	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-3			1.20446E+03	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-4			6.68579E+03	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-5			3.67135E+03	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-1	MED	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-1	LO	LO	7.57704E+03	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-2			7.06154E+03	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-3			9.33072E+03	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-4			5.96692E+04	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-5			3.10857E+04	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-1	LO	HI	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-2			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-3			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-4			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00
2-5			0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00	0.00000E+00






**Filter 0**



**Filter 1**




**Relative spectral response for radiometer detector 1-4.**




Relative spectral response for radiometer detector 1-4 (cont).







Relative spectral response for radiometer focal plane 2.




**Radiometer out-of-band rejection, focal plane 1, filter 0.**




**Radiometer out-of-band rejection, focal plane 1, filter 1.**




**Radiometer out-of-band rejection, focal plane 1, filter 2.**





**Radiometer out-of-band rejection, focal plane 1, filter 3.**




Radiometer out-of-band rejection, focal plane 1, filter 5.



Radiometer out-of-band rejection, focal plane 1, filter 7.




**Radiometer out-of-band rejection, focal plane 2.**



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

RMS noise history for radiometer detector 1-1.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

RMS noise history for radiometer detector 1-2.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.

### Chopper Off




Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.

### Chopper On


**RMS noise history for radiometer detector 1-3.**





Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

**RMS noise history for radiometer detector 1-4.**



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

**RMS noise history for radiometer detector 1-5.**



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

**RMS noise history for radiometer detector 1-6.**



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

RMS noise history for radiometer detector 1-7.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

**RMS noise history for radiometer detector 1-8.**



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

**RMS noise history for radiometer detector 2-1.**



Gain = HI ( $\times 100$ ), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI ( $\times 100$ ), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

**RMS noise history for radiometer detector 2-2.**



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.

### Chopper Off




Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.

### Chopper On


**RMS noise history for radiometer detector 2-3.**





Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

RMS noise history for radiometer detector 2-4.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

RMS noise history for radiometer detector 2-5.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 1-1.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 1-2.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 1-3.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 1-4.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 1-5.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.

### Chopper Off




Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.

### Chopper On


Offset history for radiometer detector 1-6.





Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 1-7.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 1-8.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 2-1.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 2-2.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 2-3.



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper Off



Gain = HI (x100), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 2-4.



Gain = HI ( $\times 100$ ), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.





### Chopper Off



Gain = HI ( $\times 100$ ), Bias = HHHH, FW 4, Sept 1988 - Feb 1992.


### Chopper On

Offset history for radiometer detector 2-5.




**Radiometer noise flux versus band pass for filter 0**  
 (chopper on, extended area source - order on curve labels is bias - gain).







Detector 1-5



Detector 1-7







Detector 1-6







Detector 1-8





Radiometer noise flux versus band pass for filter 0  
(chopper on, extended area source - order on curve labels is bias - gain).







**Radiometer noise flux versus band pass for filter 1**  
 (chopper on, extended area source - order on curve labels is bias - gain).







Radiometer noise flux versus band pass for filter 1  
(chopper on, extended area source - order on curve labels is bias - gain).




**Radiometer noise flux versus band pass for filter 2**  
(chopper on, extended area source - order on curve labels is bias - gain).




**Radiometer noise flux versus band pass for filter 2**  
(chopper on, extended area source - order on curve labels is bias - gain).




Radiometer noise flux versus band pass for filter 3  
(chopper on, extended area source - order on curve labels is bias - gain).




Detector 1-5



Detector 1-7







Detector 1-6







Detector 1-8

Radiometer noise flux versus band pass for filter 3  
(chopper on, extended area source - order on curve labels is bias - gain).




Radiometer noise flux versus band pass for filter 5  
(chopper on, extended area source - order on curve labels is bias - gain).







**Radiometer noise flux versus band pass for filter 5**  
(chopper on, extended area source - order on curve labels is bias - gain).




Detector 1-1



Detector 1-3




Detector 1-2




Detector 1-4


Radiometer noise flux versus band pass for filter 6  
(chopper on, extended area source - order on curve labels is bias - gain).




Detector 1-5



Detector 1-7







Detector 1-6




Detector 1-8


Radiometer noise flux versus band pass for filter 6  
(chopper on, extended area source - order on curve labels is bias - gain).




Radiometer noise flux versus band pass for filter 7  
(chopper on, extended area source - order on curve labels is bias - gain).




Detector 1-5



Detector 1-7




Detector 1-6




Detector 1-8


Radiometer noise flux versus band pass for filter 7  
(chopper on, extended area source - order on curve labels is bias - gain).




Detector 2-1



Detector 2-3




Detector 2-2




Detector 2-4

Radiometer noise flux versus band pass  
(chopper on, extended area source - order on curve labels is bias - gain).




Detector 2-5

Radiometer noise flux versus band pass  
(chopper on, extended area source - order on curve labels is bias - gain).




RMS noise history for interferometer detector 1.




RMS noise history for interferometer detector 2.






RMS noise history for interferometer detector 3.




RMS noise history for interferometer detector 4.




**RMS noise history for interferometer detector 5.**





Offset history for interferometer detector 3.



Offset history for interferometer detector 4.

